

A

B

C

D

A

B

C

D

REVISIONS				
DCN	REV	DESCRIPTION	DATE	APPROVED
PLC-IQ	A	INITIAL RELEASE	29 JUL 2007	TCG
105623	B	ADD COMM CARD POWER CONNECTIONS	22 SEP 2008	TCG
106061	C	NOT FOR 120V, UPDATE FILTS, ALLOW 6AWG 35A	19 DEC 2011	TCG
106179	D	CHANGE 40A OUTPUT BREAKER TO 35A	20 AUG 2012	TCG
106471	E	REDRAWN AND UPDATED	19 FEB 2014	TCG
108061	F	DIGITAL CONTROL BOARD, PROTOCOL BOARD	02 SEP 2020	TCG
108082	G	DC PWR TO D1 ANODE, UPDATE J4 SIGNAL NAMES	07 JUL 2021	TCG




TABLE 2

OUTPUT	C3-C6	C7	L1	L2	R3	R4	CB2	D1, D2	PWR WIRES	GND WIRE
24V 16A	1X 68000uF 50V	68000uF 50V	602230	602275	1K 1W	50 OHM 50 W	20A 60VDC	300280	10 AWG	10 AWG
24V 25A	1X 68000uF 50V	68000uF 50V	602234	602278	1K 1W	50 OHM 50 W	35A 60VDC	300296	10 AWG	10 AWG
24V 35A	2X 68000uF 50V	68000uF 50V	602239	602281	1K 1W	50 OHM 50 W	45A 60VDC	300296	8 OR 6 AWG	10 AWG
24V 50A	2X 68000uF 50V	68000uF 50V	602243	602284	1K 1W	50 OHM 50 W	70A 60VDC	300285	6 AWG	6 AWG
24V 75A	2X 68000uF 50V	68000uF 50V	602247	602287	1K 1W	50 OHM 50 W	100A 60VDC	300285	4 AWG	6 AWG
24V 100A	3X 68000uF 50V	68000uF 50V	602250	602289	1K 1W	50 OHM 50 W	125A 60VDC	300286	2 AWG	6 AWG
24V 150A	4X 68000uF 50V	68000uF 50V	602253	602281	1K 1W	50 OHM 50 W	200A 125VDC	300286	2X 4 AWG	6 AWG
48V 12A	1X 47000uF 63V	47000uF 63V	602226	602212	3.3K 2W	150 OHM 50 W	15A 60VDC	300280	10 AWG	10 AWG
48V 16A	1X 47000uF 63V	47000uF 63V	602231	602212	3.3K 2W	150 OHM 50 W	20A 60VDC	300280	10 AWG	10 AWG
48V 25A	1X 47000uF 63V	47000uF 63V	602235	602213	3.3K 2W	150 OHM 50 W	35A 60VDC	300296	10 AWG	10 AWG
48V 35A	2X 47000uF 63V	47000uF 63V	602240	602214	3.3K 2W	150 OHM 50 W	45A 60VDC	300296	8 OR 6 AWG	10 AWG
48V 50A	2X 47000uF 63V	47000uF 63V	602244	602215	3.3K 2W	150 OHM 50 W	70A 60VDC	300285	6 AWG	6 AWG
48V 75A	3X 47000uF 63V	47000uF 63V	602248	602216	3.3K 2W	150 OHM 50 W	100A 60VDC	300285	4 AWG	6 AWG
48V 100A	4X 47000uF 63V	47000uF 63V	602251	602217	3.3K 2W	150 OHM 50 W	125A 60VDC	300286	2 AWG	6 AWG

NOTES

- OUTPUT CONFIGURATION FOR 24V AND 48V MODELS WITH TWO STAGE OUTPUT FILTER AND OUTPUT BLOCKING DIODES
- C3-C7, CB2, D1, D2, L1, L2, R3, AND R4 VARY WITH OUTPUT RATING. SEE TABLE 2.
- CONTROL AND SENSE HARNESSSES ARE 22 AWG MINIMUM. SEE TABLE 2 FOR DOOR GROUND AND OUTPUT POWER WIRES.
- 24V 6A, 24V 12A, AND 48V 6A MODELS MEET LOW RIPPLE REQUIREMENTS USING A SINGLE STAGE FILTER. THOSE MODELS DO NOT USE TWO STAGE FILTERS.

PROPRIETARY INFORMATION		APPROVALS		STORED ENERGY SYSTEMS LONGMONT, CO	
THIS DRAWING AND DATA EMBODY PROPRIETARY INFORMATION WHICH IS THE CONFIDENTIAL PROPERTY OF STORED ENERGY SYSTEMS LLC (SENS) AND WHICH SHALL NOT BE COPIED, REPRODUCED OR DISCLOSED TO OTHERS.		DESIGNER		WD, I, Q, OUTPUT, 24-48V, 2 STG, DIO RECTIFIER, FILTER AND POWER OUTPUT	
		CHECKER			
		ENGINEER		SIZE	DATE
		T. GROUT		C	07 JUL 2021
© 2021 STORED ENERGY SYSTEMS, LLC		FILE: WD_00557.SCHDOC		SHEET	2 OF 3